2 CALL MANAGEMENT  1 Play Current Personal Greeting 2 Block All Calls 4 Select Next Personal Greeting 5 Record Current Personal Greeting	4 CHANGE NOTIFICATION 1 Notification Status 2 Enable All Notification 3 Block Notification 4 Change Notification Number  5 CHANGE USER SETUP	Quick Reference Card  Name: Telephone Extension: To Log In To USER MODE  • Call Receptionist from inside:
3 DISTRIBUTION LIST MANAGEMENT 1 Review First Member 2 Review Current Member 3 Remove All Members From List 4 Remove Current User From List 5 Review Last Member 6 Create or Select List Number	1 Change Password 2 Record Name 3 Review Name 4 Change Message Playback Order 5 Change Directory Listing 6 Review Directory Listing	from outside:         Enter System Access Code:         Enter User ID:         Enter Password:          USER MENU          Message Management         Call Management         Distribution List Manager          Change Notification
7 Add New User ID to List 8 Add New Network ID to List  1 Message Management	7 QUICK SETUP  8 SYSTEM DATE AND TIME  0 LOG OUT OF USER MODE  1 MESSAGE MANAGEMENTctnd	5 CHANGE INDITION 5 CHANGE USER SETUP 7 QUICK SETUP 8 SYSTEM ADMINISTRATION  1 MESSAGE MANAGEMENTctnd
1 Play Next Message	4 Erase Message Just Heard	6 Reply or Send New Message
2 Replay Message Just Heard	5 Forward Message Just Heard	Send Message
3 Advanced Options	User or Distribution List.	Record Message
Play Previous Message	1 Forward Message	Review Message
3 Quick Messaging	Record Message Prefix	Send with Delivery Options
4 Erase All Messages	Review Message Prefix	1 Deliver Message
UnErase All Messages	Forward with Special Deliver Options	2 Set Private
→ 6 Check Unheard Sent Messages  7 Play First Message	Deliver Message	3 Set Certified
Play First Messagectnd	Set Private	4 Set Urgent
	3 Set Certified	5 Set Future Delivery  → 8 Reset Delivery Options
Message Playback Controls	→ 4 Set Urgent     → 5 Set Future Delivery	9 Cancel Delivery
Rewind 8 Fast-Forward ★ Pause	8 Reset Delivery Options	5 Append to Message
User Tips	9 Cancel Delivery	→ 6 Select Personal List Number
Press 0 to log out from anywhere.		Select User ID
Press 9 to return to previous menu.	5 Append to Message Prefix	Select Network ID
Press # to terminate any recording.	6 Select Personal List Number	7 Replay From End
<ul> <li>Press  to replay menu options.</li> </ul>	7 Select User ID 8 Select Network ID	8 Power Playback
	O Select NetWORK ID	D FOWEI Flayback